

⚡ MOVELITE 35 MOTOR WT • DCT • RTS

Size L265mm (10⁷/₁₆"") x w93mm (3¹¹/₁₆"") x d53mm (2¹/₁₆"")
 Power Supply 90 - 255V, 50/60 Hz
 Noise < 41 dBA
 Max Length 6m (19.5')
 Max Weight 35kg (77lb)
 Control WT, DCT, RTS

WT Motor 4 core cable
 Mains switching
 Controlled with automation systems or hard wired wall switch

DCT Motor 3 core cable
 Dry contact, Volt free switching
 Controlled with automation systems via volt free or RTS / volt free hard wired wall switch

RTS Motor 3 core cable
 Built in radio receiver
 Dry contact, Volt free switching
 Controlled with Somfy remote or app control options / automation systems via volt free or RTS / volt free hard wired wall switch



MOTOR FEATURES	Movelite 35 WT	Movelite 35 DCT	Movelite 35 RTS
Soft Start	✗	✗	✗
Soft Stop	✗	✗	✗
Intermediate Position	✓	✗	✓
Manual Override	✓	✓	✓
Touch Motion	✓	✗	✓
Automatic Limits on End Stop	✓	✓	✓
Back Release	✗	✗	✗
Adjustable Limits	✓	✗	✓
Speed Control & Adjustment	✗	✗	✗
Set via 3 NO Dry Contact Setting tool	✓	✓	✓
Setting with button on motor	✗	✗	✗
Motor direction change	✓	✓	✓
DCT ergonomics setting 2 or 3 buttons	✓	✗	✓
Factory reset	✓	✓	✓
LED indicators	✗	✗	✗
Modulability	✗	✗	✗
Silent mode	✗	✗	✗
Buzzer indicators	✗	✗	✗
Remote control	✗	✗	✓
App control	✗	✗	✓